

## Adafruit Gemma M0

Created by lady ada



Last updated on 2021-04-06 06:22:43 PM EDT

## Guide Contents

Guide Contents	2
Overview	8
Guided Tour	11
Pinouts	13
JST Battery Input	13
Power Pads	13
Input/Output Pads	13
Common to all pads	13
Unique pad capabilities	14
The onboard Dotstar LED	14
Secret SWD and Reset Pads	14
Windows Driver Installation	16
Manual Driver Installation	18
What is CircuitPython?	19
CircuitPython is based on Python	19
Why would I use CircuitPython?	19
CircuitPython	21
Set up CircuitPython Quick Start!	21
Further Information	23
Gemma Default Zip Install	23
Installing Mu Editor	26
Download and Install Mu	26
Using Mu	26
Creating and Editing Code	28
Creating Code	28
Editing Code	30
Your code changes are run as soon as the file is done saving.	30
1. Use an editor that writes out the file completely when you save it.	31
2. Eject or Sync the Drive After Writing	32
Oh No I Did Something Wrong and Now The CIRCUITPY Drive Doesn't Show Up!!!	32
Back to Editing Code...	32
Exploring Your First CircuitPython Program	32
Imports & Libraries	33
Setting Up The LED	33
Loop-de-loops	33
What Happens When My Code Finishes Running?	34
What if I don't have the loop?	34
More Changes	34
Naming Your Program File	35
Connecting to the Serial Console	36
Are you using Mu?	36
Setting Permissions on Linux	37
Using Something Else?	37
Interacting with the Serial Console	38
The REPL	41
Returning to the serial console	44
CircuitPython Libraries	45

Installing the CircuitPython Library Bundle	46
Example Files	47
<b>Copying Libraries to Your Board</b>	<b>47</b>
Example: ImportError Due to Missing Library	47
Library Install on Non-Express Boards	49
Updating CircuitPython Libraries/Examples	49
<b>Frequently Asked Questions</b>	<b>50</b>
I have to continue using an older version of CircuitPython; where can I find compatible libraries?	50
Is ESP8266 or ESP32 supported in CircuitPython? Why not?	50
How do I connect to the Internet with CircuitPython?	50
Is there asyncio support in CircuitPython?	50
My RGB NeoPixel/DotStar LED is blinking funny colors - what does it mean?	50
What is a MemoryError?	51
What do I do when I encounter a MemoryError?	51
Can the order of my import statements affect memory?	51
How can I create my own .mpy files?	51
How do I check how much memory I have free?	51
Does CircuitPython support interrupts?	51
Does Feather M0 support WINC1500?	51
Can AVRs such as ATmega328 or ATmega2560 run CircuitPython?	52
Commonly Used Acronyms	52
<b>Uninstalling CircuitPython</b>	<b>53</b>
Backup Your Code	53
<b>Moving Circuit Playground Express to MakeCode</b>	<b>53</b>
<b>Moving to Arduino</b>	<b>54</b>
<b>Troubleshooting</b>	<b>56</b>
<b>Always Run the Latest Version of CircuitPython and Libraries</b>	<b>56</b>
I have to continue using CircuitPython 5.x, 4.x, 3.x or 2.x, where can I find compatible libraries?	56
<b>CPLAYBOOT, TRINKETBOOT, FEATHERBOOT, or GEMMABOOT Drive Not Present</b>	<b>56</b>
You may have a different board.	56
MakeCode	56
Windows 10	57
Windows 7	57
MacOS	57
<b>Windows Explorer Locks Up When Accessing boardnameBOOT Drive</b>	<b>58</b>
<b>Copying UF2 to boardnameBOOT Drive Hangs at 0% Copied</b>	<b>58</b>
<b>CIRCUITPY Drive Does Not Appear</b>	<b>58</b>
<b>Serial Console in Mu Not Displaying Anything</b>	<b>58</b>
<b>CircuitPython RGB Status Light</b>	<b>59</b>
<b>ValueError: Incompatible .mpy file.</b>	<b>60</b>
<b>CIRCUITPY Drive Issues</b>	<b>60</b>
Easiest Way: Use <code>storage.erase_filesystem()</code>	60
Old Way: For the Circuit Playground Express, Feather M0 Express, and Metro M0 Express:	61
Old Way: For Non-Express Boards with a UF2 bootloader (Gemma M0, Trinket M0):	62
Old Way: For non-Express Boards without a UF2 bootloader (Feather M0 Basic Proto, Feather Adalogger, Arduino Zero):	62
<b>Running Out of File Space on Non-Express Boards</b>	<b>62</b>
Delete something!	62
Use tabs	63
MacOS loves to add extra files.	63
Prevent & Remove MacOS Hidden Files	63

Copy Files on MacOS Without Creating Hidden Files	64
Other MacOS Space-Saving Tips	64
Device locked up or boot looping	65
Welcome to the Community!	67
Adafruit Discord	67
Adafruit Forums	68
Adafruit Github	69
ReadTheDocs	70
CircuitPython Essentials	71
CircuitPython Pins and Modules	72
CircuitPython Pins	72
import board	72
I2C, SPI, and UART	73
What Are All the Available Names?	74
Microcontroller Pin Names	75
CircuitPython Built-In Modules	75
CircuitPython Built-Ins	76
Thing That Are Built In and Work	76
Flow Control	76
Math	76
Tuples, Lists, Arrays, and Dictionaries	76
Classes, Objects and Functions	76
Lambdas	76
Random Numbers	76
CircuitPython Digital In & Out	77
Find the pins!	78
Read the Docs	80
CircuitPython Analog In	81
Creating the analog input	81
get_voltage Helper	81
Main Loop	81
Changing It Up	82
Wire it up	82
Reading Analog Pin Values	85
CircuitPython Analog Out	86
Creating an analog output	86
Setting the analog output	86
Main Loop	86
Find the pin	87
CircuitPython PWM	91
PWM with Fixed Frequency	91
Create a PWM Output	92
Main Loop	92
PWM Output with Variable Frequency	92
Wire it up	93
Where's My PWM?	98
CircuitPython Servo	99
Servo Wiring	99
Standard Servo Code	101
Continuous Servo Code	101
CircuitPython Cap Touch	103
Create the Touch Input	103

Main Loop	103
Find the Pin(s)	104
<b>CircuitPython Internal RGB LED</b>	<b>108</b>
Create the LED	108
Brightness	109
Main Loop	109
Making Rainbows (Because Who Doesn't Love 'Em!)	110
Circuit Playground Express Rainbow	111
<b>CircuitPython NeoPixel</b>	<b>113</b>
Wiring It Up	113
The Code	114
Create the LED	115
NeoPixel Helpers	116
Main Loop	116
NeoPixel RGBW	116
Read the Docs	117
<b>CircuitPython DotStar</b>	<b>119</b>
Wire It Up	119
The Code	120
Create the LED	122
DotStar Helpers	123
Main Loop	123
Is it SPI?	123
Read the Docs	124
<b>CircuitPython UART Serial</b>	<b>125</b>
The Code	125
Wire It Up	126
Where's my UART?	129
Trinket M0: Create UART before I2C	130
<b>CircuitPython I2C</b>	<b>132</b>
Wire It Up	132
Find Your Sensor	135
I2C Sensor Data	136
Where's my I2C?	137
<b>CircuitPython HID Keyboard and Mouse</b>	<b>139</b>
CircuitPython Keyboard Emulator	139
Create the Objects and Variables	140
The Main Loop	141
<b>CircuitPython Mouse Emulator</b>	<b>141</b>
Create the Objects and Variables	143
CircuitPython HID Mouse Helpers	143
Main Loop	143
<b>DHT CircuitPython Code</b>	<b>145</b>
<b>Adafruit CircuitPython Module Install</b>	<b>145</b>
Wiring	145
Usage	146
Example Code	147
<b>CircuitPython CPU Temp</b>	<b>149</b>
<b>CircuitPython Storage</b>	<b>150</b>
Logging the Temperature	151
<b>CircuitPython Expectations</b>	<b>154</b>
<b>Always Run the Latest Version of CircuitPython and Libraries</b>	<b>154</b>

I have to continue using CircuitPython 3.x or 2.x, where can I find compatible libraries?	154
Switching Between CircuitPython and Arduino	154
The Difference Between Express And Non-Express Boards	154
Non-Express Boards: Gemma, Trinket, and QT Py	155
Small Disk Space	155
No Audio or NVM	155
Differences Between CircuitPython and MicroPython	155
Differences Between CircuitPython and Python	155
Python Libraries	155
Integers in CircuitPython	155
Floating Point Numbers and Digits of Precision for Floats in CircuitPython	156
Differences between MicroPython and Python	156
MakeCode	157
What is MakeCode Maker?	158
How is it related to makecode.adafruit.com ?	158
Is it open source?	158
Editing Blocks	161
Blinky!	161
Editing JavaScript	163
Blocks to JavaScript	163
Downloading and Flashing	164
Step 1: Connect your board via USB	164
Step 2: Test your code in the simulator	164
Step 3: Download and flash your code	165
General Steps to copy over your program (not specific to any Operating system)	165
Saving and Sharing	166
Extracting your code from the board	166
Sharing	166
Custom Extensions	167
Account setup	167
Commit and push	168
Conflicts	169
Testing your package	169
Arduino IDE Setup	171
<a href="https://adafruit.github.io/arduino-board-index/package_adafruit_index.json">https://adafruit.github.io/arduino-board-index/package_adafruit_index.json</a>	172
Using with Arduino IDE	174
Install SAMD Support	174
Install Adafruit SAMD	174
Install Drivers (Windows 7 & 8 Only)	176
Blink	177
Successful Upload	178
Compilation Issues	178
Manually bootloading	179
Ubuntu & Linux Issue Fix	179
Adapting Sketches to M0 & M4	180
Analog References	180
Pin Outputs & Pullups	180
Serial vs SerialUSB	180
AnalogWrite / PWM on Feather/Metro M0	181

analogWrite() PWM range	182
analogWrite() DAC on A0	182
Missing header files	182
Bootloader Launching	182
Aligned Memory Access	182
Floating Point Conversion	183
How Much RAM Available?	183
Storing data in FLASH	183
Pretty-Printing out registers	183
M4 Performance Options	184
CPU Speed (overclocking)	184
Optimize	184
Cache	185
Max SPI and Max QSPI	185
Enabling the Buck Converter on some M4 Boards	185
Downloads	186
Files:	186
Schematic & Fabrication Print	186
UF2 Bootloader Details	188
Entering Bootloader Mode	189
Using the Mass Storage Bootloader	191
Using the BOSSA Bootloader	192
Windows 7 Drivers	192
Verifying Serial Port in Device Manager	192
Running bossac on the command line	194
Using bossac Versions 1.7.0, 1.8	194
Using bossac Versions 1.9 or Later	194
Updating the bootloader	195
Getting Rid of Windows Pop-ups	196
Making your own UF2	197
Installing the bootloader on a fresh/bricked board	197













































































































































































































































































































































































































































